# **Turinys**

# IP parametrų nustatymas

Kaip nustatyti IP adresus, naudojant Windows 7	L
Kaip nustatyti IP adresus, naudojant Windows 8.x	7
Kaip nustatyti IP adresus, naudojant Windows XP1	1

Kaip	prijungti	belaidį	maršrutizatorių	(Wi-Fi	<b>)</b> 1	14
------	-----------	---------	-----------------	--------	------------	----

## IP parametrų nustatymas

Jungiantis prie Balticum interneto, IP parametrų įvesti nereikia, IP adresai priskiriami abonentui automatiškai (DHCP).

# Kaip nustatyti IP adresus, naudojantis Windows 7

## I variantas

Norėdami nustatyti automatinius IP parametrus **Windows 7** operacinėje sistemoje, pasirinkus *Start* mygtuką reikia paieškos laukelyje įvesti *Network and sharing*, ir pasirinkti *Network and Sharing Center*.



Sekančiame žingsnyje paspauskite *Change adapter settings*:



Atsidariusiame lange pažymėkite ikoną *Local Area Connection*, spustelkite dešinį pelės klavišą ir išsirinkę paspauskite ant *Properties*:

	Control Panel  Network	and Internet 🕨 Network
Organize 🔻	Disable this network device	Diagnose this conne
	ocal Area Connection etwork tel(R) 82578DC Gigabit Network	VMware Net Unidentified VMware Virt
9	Disable <b>Status</b> Diagnose	
•	Bridge Connections	
0	Delete	
•	Rename	
8	Properties	

Atsidariusiame lange raskite punktą *Internet Protocol Version 4 (TCP/IPv4)*, pažymėkite ir vėl paspauskite *Properties* mygtuką:

Local Area Connection Properties
Networking Sharing
Connect using:
Intel(R) 82578DC Gigabit Network Connection
Configure
Rile and Printer Sharing for Microsoft Networks
✓ ▲ Internet Protocol Version 6 (TCP/IPv6)
Internet Protocol Version 4 (TCP/IPv4)
Link-Layer Topology Discovery Mapper I/O Driver
Link-Layer Topology Discovery Responder
Install Uninstall Properties
Transmission Control Protocol/Internet Protocol. The default wide area network protocol that provides communication across diverse interconnected networks.
OK Cancel

Atsidariusiame naujame lange reikia nustatyti automatinius IP adresus. Jeigu anksčiau IP adresai buvo įvesti, reikia pasirinkti punktus **Obtain an IP address automatically**, **Obtain DNS server address automatically**, tuomet ankstesnieji IP adresai išsitrins.

eneral	Alternate Configura	ation				
You car this cap for the	n get IP settings assi pability. Otherwise, y appropriate IP settir	igned automa you need to a ngs.	atically if ask your r	your n networ	etwork s k admini	supports strator
٥ (	btain an IP address a	automatically				
OU	se the following IP ac	ddress:				
IP a	ddress:	[				
Subr	net mask:	[				
Defa	ult gateway:	[		4		
() O	btain DNS server add	dress automa	atically			
-OU:	se the following DNS	server addre	esses:			
Pref	erred DNS server:					
Alter	mate DNS server:	[	3	*	*	
V	alidate settings upor	n exit			Adva	anced

Paspauskite **OK**, viską uždarykite ir naudokitės internetu. Atlikus šiuos veiksmus, rekomenduojame perkrauti kompiuterį.

### II variantas

### Pasirinkite Start mygtuką ir paspauskite Control Panel:



#### Atsidariusiame lange pasirinkite ir paspauskite Network and Sharing Center:



## Paspauskite ant *Change adapter settings*:

				_ <b>D</b> X
🕒 🗢 🖳 🗸 Kontrol Panel 🔸	All Control Panel Items > Network and Sharing	g Center	•	🍫 Search Con 🖇
Control Panel Home	View your basic network informat	tion and set up con	nections	
Change adapter settings Change advanced sharing settings	WIN-JU7Q1D9J4NO (This computer)	Network	Internet	See full map
	View your active networks		Cor	nect or disconnect
	Network Public network	Access typ Connection	oe: Internet ons: 🏺 Local Area Co	nnection
	Change your networking settings			
	Set up a new connection or netwo Set up a wireless, broadband, dial-	ork -up, ad hoc, or VPN conn	ection; or set up a rou	ter or access point.
	Connect to a network Connect or reconnect to a wireless	s, wired, dial-up, or VPN r	network connection.	
	Choose homegroup and sharing of Access files and printers located o	options In other network compute	ers, or change sharing	settings.
See also	Troubleshoot problems		,,,	
HomeGroup	Diagnose and repair network prob	ilems, or get troubleshoot	ting information.	
Internet Options				
Windows Firewall				

Pasirinkę ikoną *Local Area Connection* paspauskite dešinį pelės klavišą ir pasirinkite *Properties*:



Atsidariusiame lange raskite punktą *Internet Protocol Version 4 (TCP/IPv4)*, pažymėkite ir paspauskite *Properties* mygtuką:

Local Area Connection Properties
Networking
Connect using:
Intel(R) PRO/1000 MT Network Connection
Configure This connection uses the from the sense of t
Install Uninstall Properties
Transmission Control Protocol/Internet Purchase area network protocol that provide area network protocol that provide across diverse interconnected network
OK Cancel

Atsidariusiame naujame lange reikia nustatyti automatinius IP adresus.

Jeigu anksčiau IP adresai buvo įvesti, reikia pasirinkti punktus *Obtain an IP address automatically*, *Obtain DNS server address automatically*, tuomet ankstesnieji IP adresai išsitrins.

General	Alternate Configuration					
You car this cap for the	n get IP settings assigned a pability. Otherwise, you nee appropriate IP settings.	utomatically ed to ask yo	rify urn	our n etwor	etwork s k admini	supports strator
() O	btain an IP address automa	tically				
	se the following IP address:					
IP a	ddress:					
Subr	net mask:			2		
Defa	ult gateway:			3	i.	
() O	btain DNS server address a	utomatically				
OU	se the following DNS server	addresses:				
Pref	erred DNS server:					
Alter	mate DNS server:				*	
V	alidate settings upon exit				Adva	anced

Paspauskite **OK**, viską uždarykite ir naudokitės internetu. Atlikus šiuos veiksmus, rekomenduojame perkrauti kompiuterį.

# Kaip nustatyti IP adresus, naudojant Windows 8.x

Pelės kursorių nuveskite į darbalaukio dešinįjį viršutinį kampą ir laikykite, kol pasirodys meniu su pasirinkimu, pasirinkite **Settings**:



## Pasirinkite *Control Panel*:



#### Atsidariusiame lange pasirinkite kategoriją Small icons:



### Pasirinkite Network and Sharing Center:



# Kitame lange paspauskite *Change adapter settings*:

	Network and Sharing G	enter	
Control Panel Home	tems + Network and Sharing Center your basic network information or active networks		trol Pastel "P
Change adapter settings Change advanced sharing settings	Wifi blic network	Access type: No Internet : Connections: ﷺ Wi-Fi (Zen W	access Vilio
	Set up a new connection or network     Set up a new connection or network     Set up a broadband, dial-up, or VPN co     Troubleshoot problems     Diagnose and repair network problems	onnection; or set up a router or access po , or get troubleshooting information.	int.
See also HomeGroup Internet Options Windows Firewall			

Dešiniuoju pelės klavišu spustelkite ant ikonos *Local Area Connection* ir pasirinkite **Properties**:

Local Area Connection	er ong to a connection		S.	
Network Intel(II) PRO/2000 MT Network (	<ul> <li>Disable</li> <li>Status</li> <li>Diagnose</li> <li>Bridge Connections</li> <li>Create Shortcut</li> <li>Delete</li> <li>Rename</li> <li>Properties</li> </ul>			

Atsidariusiame lange raskite punktą *Internet Protocol Version 4 (TCP/IPv4)*, pažymėkite ir paspauskite *Properties* mygtuką:

Local Area Connection Properties
Networking
Connect using:
Intel(R) PRO/1000 MT Network Connection
Configure This connection uses the free series series series series to the series s
Install Uninstall Properties
Description Transmission Control Protocol/Internet Provide area network protocol that provide across diverse interconnected network
OK Cancel

Atsidariusiame naujame lange reikia nustatyti automatinius IP adresus.

Jeigu anksčiau IP adresai buvo įvesti, reikia pasirinkti punktus *Obtain an IP address automatically*, *Obtain DNS server address automatically*, tuomet ankstesnieji IP adresai išsitrins.

ocricial	Alternate Configuration				
You car this cap for the	n get IP settings assigned aut bability. Otherwise, you need appropriate IP settings.	tomatically if to ask your	your n networ	etwork s k admini	upports strator
() O	otain an IP address automatic	cally			
OUs	e the following IP address:				
IP ad	ddress:		- 2		
Subr	net mask:				
Defa	ult gateway:	4	4	¥.	
() O	otain DNS server address aut	omatically			
	e the following DNS server a	ddresses:			
Prefi	erred DNS server:				
Alter	nate DNS server:		+		
V	alidate settings upon exit			Adva	nced

Paspauskite **OK**, viską uždarykite ir naudokitės internetu. Atlikus šiuos veiksmus, rekomenduojame perkrauti kompiuterį.

# Kaip nustatyti IP adresus, naudojant Windows XP

Darbalaukyje paspauskite mygtuką Start ir pasirinkite Control Panel:



Pasirinkite Network and Internet Connections:



Pasirinkite ikoną *Local Area Connection*, spustelkite dešinį pelės klavišą, pasirinkite *Properties*:

S Network Connections	
<u>File E</u> dit <u>V</u> iew F <u>a</u> vorites <u>T</u> ools Adva <u>n</u> ced	Help 🥂
G Back 🝷 🕥 🚽 🏂 🔎 Search 🎼 F	olders
Address 🔇 Network Connections	💌 🄁 Go
Network Tasks       Image: Connection         Image: Create a new connection       Image: Create a new connection         Image: Create a new connection       Image: Create a new connection         Image: Change Windows Firewall settings       Image: Create a new connection         Image: Change Windows Firewall settings       Image: Create a new connection         Image: Change settings       Image: Create a new connection         Image: Rename this connection       Image: Connection         Image: Change settings of this connection       Image: Create a new connection         Image: Change settings of this connection       Image: Change settings of this connection	Jh-Speed Internet Local Area Connection Connected 3Com 3C920 Integrated Fast
Other Places       Image: Control Panel         Image: My Network Places       Image: My Documents         Image: My Computer       Image: My Computer         Image: Details       Image: Content of the second secon	

# Atsidariusiame langelyje paspauskite **Properties**:

🕹 Local Area Conn	ection Status		?×
General Support			
Connection			
Status:		Connecte	d
Duration:		02:54:2	1
Speed:		100.0 Mbp	IS
Activity	Sent —	Received	d
Bytes:	3,070,463	10,529,43	1
Properties	<u>D</u> isable		
			se

Sąraše pasirinkite Internet Protocol (TCP/IP), pažymėkite ir paspauskite mygtuką Properties:

🕂 Local Area Connection Properties 🛛 🔹 💽
General Authentication Advanced
Connect using:
B 3Com 3C920 Integrated Fast Etherne
This connection uses the following items:
✓       ■ Client for Microsoft Networks         ✓       ₽ File and Printer Sharing for Microsoft Networks         ✓       ₽ QoS Packet Scheduler         ✓       > Internet Protocol (TCP/IP)
Install         Uninstall         Properties           Description
Transmission Control Protocol/Internet Protocol. The default wide area network protocol that provides communication across diverse interconnected networks.
<ul> <li>✓ Show icon in notification area when connected</li> <li>✓ Notify me when this connection has limited or no connectivity</li> </ul>
OK Cancel

Pažymėkite punktus *Obtain an IP address automatically, Obtain DNS server address automatically* ir paspauskite Ok, kad išsaugotume nustatymus.

2822322	Alternate Configuration					
You car this car for the	n get IP settings assigned a bability. Otherwise, you nee appropriate IP settings.	automatically ed to ask yo	if y ur ne	our n etwor	etwork kadmin	supports iistrator
() O	otain an IP address automa	atically				
OU	e the following IP address:					
IP a	ddress:			2		
Subr	net mask:			$\mathbf{x}$		
Defa	ult gateway:			÷.	1	
() O	otain DNS server address a	utomatically				
OU	e the following DNS server	addresses:				
Pref	erred DNS server:					
Alter	nate DNS server:				12	
	alidate settings upon exit				Adv	anced

Atlikus šiuos pakeitimus, rekomenduojame perkrauti kompiuterį.

# Kaip prie Balticum Interneto prijungti belaidį maršrutizatorių (Wi-Fi)

Interneto kabelį įjunkite į belaidį maršrutizatorių (kabelis jungiamas į WAN jungtį).



Darbalaukyje, įrankių juostoje susiraskite bevielio tinklo ikoną, paspauskite ją. Bevielių tinklų sąraše susiraskite savo Bevielį tinklą, pasirinkite jį ir paspauskite **Connect**.

Sukonfigūruotas belaidis maršrutizatorius turi prisijungimo slaptažodį, kurį reikia įvesti. Kai kurie maršrutizatoriai jau būna sukonfigūruoti ir slaptažodis užrašytas ant maršrutizatoriaus etiketės.

Kilus sunkumams, kreipkitės į mūsų IT specialistus tel. 8 46 390716.